



DigiFarm

372 VRS setup with Pro 700

- Ensure that the 372 NTRIP cable is installed in Port B of the receiver
 - ◆ From the run screens select back > Toolbox > GPS
 - tab Set the correction type to RTK
 - Set the correction level to Modem
 - Select the RTK source setup Edit icon
 - Enter the below network information
 - Username: DigiFarm assigned username
 - Password: DigiFarm assigned password
 - Server address: caster.godigifarm.com
 - Mount Point: VBN_RTCM3_TRM
 - Port Number: 3101
 - Select OK to save settings
 - Enable xFill mode
 - Select xFill setup Edit
 - Select custom
 - Enter the xFill information below
 - Frequency: 1555.8080
 - Baud Rate: 2400
 - Datum Select: NAD83
 - Select OK to save these settings