


DigiFarm

Programming FMX NMEA output using red feedback wire

Begin by installing the red wire from P/N MD3017 (when using a legacy modem) or P/N MD8117-15 (when using an elevate), into Port A or Port B.



- From the home screen, select the wrench icon > GPS receiver > Setup
 - Select the GPS output icon or tab
 - Select the correct port according to physical connection of the red wire
 - Set the message rate to 1hz
 - Set the baud rate to 38400
 - Set the maximum GGA Quality to highest value possible
 - Lat/Lon precision can stay where its defaulted
 - Select the NMEA messages tab
 - Ensure GGA is on at 1hz
 - Turn all others off